



Conekt CSR-35 Bluetooth Low-Energy (BLE)/Contactless Smartcard Reader

CONEKT™ MOBILE SMARTPHONE ACCESS CONTROL SOLUTION

With Conekt, the smartphone is the access credential

Conekt is Farpointe Data's mobile-ready access control ID solution—consisting of a smartphone wallet app, mobile credentials, and combination Bluetooth Low Energy (BLE)/contactless smartcard readers. Based upon the proven LEGIC® contactless digital radio frequency identification (RFID) platform, Conekt readers interface with a wide range of electronic access control systems by complying with either the legacy Wiegand or bi-directional Open Supervised Device Protocol (OSDP).

In addition to supporting mobile access credentials, using the BLE feature of select smartphones, Conekt readers also read traditional contactless smart cards.

Featuring easy registration, convenient mobile credentials, and multi-technology readers, Conekt is the next-generation ID solution for your electronic access control systems.

Benefits of 2.4-GHz/13.56-MHz Conekt:

- Smartphone wallet app securely stores mobile credentials
- One-time registration without disclosure of private information
- Cloud-based delivery of mobile credentials
- Readers read Conekt BLE mobile credentials as well as traditional contactless smart cards
- Supports industry standard and custom formats
- Presentation and long-range readers available

Mobile Integration as Easy at 1-2-3!

1. Smartphone wallet app to securely store mobile credentials

End users appreciate Conekt's respect for privacy—no private information, on-boarding process, or portal accounts required.

2. Mobile credentials with cloud-based delivery


With a convenient cloud-based delivery system and no physical credentials to inventory, Conekt mobile credentials are quicker and easier to order, distribute and maintain.

3. Readers combining BLE and contactless smart card technologies

Conekt allows access control manufacturers and integrators to offer customers a total solution—one that supports mobile credentials and traditional physical credentials.



Look for **Conekt** on the App Store and on Google Play



Conekt Readers & Credentials

SELECTION GUIDE

BLE/Contactless Smartcard Readers	Frequency	Read Range	Mullion Mount	Single-Gang Mount	Lifetime Warranty
CSR-35P	2.4 GHz and 13.56 MHz	up to 1.5 inches (38 mm)	•	•	•
CSR-35L	2.4 GHz and 13.56 MHz	up to 15 feet (4.6 m)	•	•	•

Credentials	Frequency	Read Range	DESFire EV2	MAXSecure™	ValidID™	Wiegand	Lifetime Warranty
CMC-2	2.4 GHz	with CSR-35P, up to 1.5 inches (38 mm)	•	•	•	•	•
		with CSR-35L, up to 15 feet (4.6 m)	•	•	•	•	•

Farpointe Data reserves the right to change specifications without notice.

© 2018 Farpointe Data, Inc. All rights reserved. Farpointe Data®, Pyramid Series Proximity®, Delta®, and Ranger® are the registered U.S. trademarks of Farpointe Data, Inc. Conekt is a trademark of Farpointe Data, Inc. MIFARE and MIFARE DESFire are registered trademarks of NXP B.V. All other trademarks are the property of their respective owners.

Farpointe Data, Inc.
1376 Borregas Avenue
Sunnyvale, CA 94089-1004 USA
Office: +1-408-731-8700
Fax: +1-408-731-8705
support@farpointedata.com

